

# FR100 Series Siren

ETSAFR100



Compact, easy to operate siren with PA function.




## FEATURES

- Full function siren for use with one or two 100 watt speakers
- Large buttons and rotary knob for easy operation even with gloves
- Up to 24 selectable tones including dedicated mechanical tone button
- Horn and manual button plus horn ring transfer input
- Hands-free operating mode
- Five year warranty

## SPECIFICATIONS

Voltage	10-30 VDC
Wattage	200 Watts
Input Current	9.5 Amps @ 13.4 VDC (100W speaker) 19 Amps @ 13.4 VDC (2 x 100W speakers)
Frequency Range	500Hz - 2000Hz (siren), 300Hz - 10,000Hz (audio)
Operating Temperature	-40°C to +50°C
Primary Operating Modes	PA, radio, manual, hands free, wail, yelp, user selectable tone, horn override, user selectable override
Dimensions	6" (152.6mm) L x 2.14" (54.3mm) H x 6.14" (156mm) D
Mount	U-bracket or console mount
Certifications	SAE J1849*, CA Title 13*, ECE R10 <i>*when used with approved SoundOff Signal speakers</i>



Scan to order  
or learn more

## CONTACT

Toll free 800.338.7337  
Direct 616.896.7100  
[soundoffsignal.com](http://soundoffsignal.com)

PO Box 206  
Hudsonville, MI 49426  
[customerservice@soundoffsignal.com](mailto:customerservice@soundoffsignal.com)